

Relays monitor voltage

Type	Design	Voltage	Secure variables							Setting			Description	Page
			Phases	Range	> U	< U	Failure	Phase sequence	Asymmetry	Delay	Hysteresis	Memory Errors		
HRN-33	1-M	from monitored	1	AC 48 - 276 V	●	●	x	x	x	●	x	x	For all types, the delay is adjustable from 0 - 10 seconds (to eliminate short-term outages or peaks). The lower voltage level (Umin) is set in % of the upper level (Umax).	70
HRN-34	1-M	from monitored	1	DC 6 - 30 V	●	●	x	x	x	●	x	x		
HRN-35	1-M	from monitored	1	AC 48 - 276 V	●	●	x	x	x	●	x	x		
HRN-37	1-M	from monitored	1	AC 24 - 150 V	●	●	x	x	x	●	x	x		
HRN-63	1-M	from monitored	1	AC 48 - 276 V	●	●	x	x	x	●	x	x		
HRN-64	1-M	from monitored	1	DC 6 - 30 V	●	●	x	x	x	●	x	x		
HRN-67	1-M	from monitored	1	AC 24 - 150 V	●	●	x	x	x	●	x	x	Second relay function (independent/parallel). Galvanically separated power supply from measuring inputs.	72
HRN-41/230V HRN-41/110V HRN-41/400V HRN-41/24V	3-M	AC 230 V AC 110 V AC 400 V AC/DC 24 V	1	AC/DC 50 V AC/DC 160 V AC/DC 500 V	●	●	x	x	x	●	●	●		
HRN-42/230V HRN-42/110V HRN-42/400V HRN-42/24V	3-M	AC 230 V AC 110 V AC 400 V AC/DC 24 V	1	AC/DC 50 V AC/DC 160 V AC/DC 500 V	●	●	x	x	x	●	●	●		
HRN-43/230V HRN-43/110V HRN-43/400V HRN-43/24V	3-M	AC 230 V AC 110 V AC 400 V AC/DC 24 V	3	AC 3 x 84 - 480 V	●	●	●	●	●	●	●	●	2 output relays, functions of the second relay may be selected (independent/parallel). Galvanically separated power supply.	74
HRN-43N/230V HRN-43N/110V HRN-43N/400V HRN-43N/24V	3-M	AC 230 V AC-110 V AC 400 V AC/DC 24 V	3	AC 3 x 48 - 276 V	●	●	●	●	●	●	●	●		
HRN-55	1-M	from monitored	3	AC 3 x 300 - 500 V	x	x	●	●	x	●	x	x	Power supply from all phases, i.e. the relay function is preserved even if one phase fails.	77
HRN-55N	1-M	from monitored	3	AC 3 x 172 - 287 V	x	x	●	●	x	●	x	x	Power supply L1-N, i.e. the relay also monitors the neutral wire interruption.	77
HRN-57	1-M	from monitored	3	AC 3 x 300 - 500 V	●	●	●	x	x	●	x	x	Power supply from all phases, i.e. the relay function is preserved even if one phase fails.	79
HRN-57N	1-M	from monitored	3	AC 3 x 172 - 287 V	●	●	●	x	x	●	x	x	Power supply L1-N, i.e. the relay also monitors the neutral wire interruption, replacement for HRN-52.	79
HRN-54	1-M	from monitored	3	AC 3 x 300 - 500 V	●	●	●	●	x	●	x	x	If the supply voltage falls below 60% of Un (OFF lower level), the relay will immediately disconnects with no delay. Power supply from all phases, i.e. the relay function is preserved even if one phase fails.	76
HRN-54N	1-M	from monitored	3	AC 3 x 172 - 287 V	●	●	●	●	x	●	x	x	If the supply voltage falls below 60% of Un (OFF lower level), the relay will immediately disconnects with no delay. Power supply L1-N, i.e. the relay also monitors the neutral wire interruption.	76
HRN-56/120 HRN-56/208 HRN-56/240 HRN-56/400	1-M	from monitored	3	AC 3 x 72 - 160 V AC 3 x 125 - 276 V AC 3 x 144 - 276 V AC 3 x 240 - 460 V	x	●	●	●	x	●	x	x	Thanks to the power supply from all three phases, the relay is operational even if one phase fails.	78
HRN-56/480 HRN-56/575	3-M	from monitored	3	AC 3 x 228 - 550 V AC 3 x 345 - 660 V	x	●	●	●	x	●	x	x		

Signal relays

MPS-1	1-M	from monitored	3	AC 3 x 50 - 253 V	x	●	●	●	x	x	x	x	Optical signaling of three-phase network.	80
-------	-----	----------------	---	-------------------	---	---	---	---	---	---	---	---	---	----

Relay for frequency monitoring

Type	Design	Supply voltage	Secure variables				Setting				Description	Page
			Phases	Frequency Range	Frequency [^]	Frequency ^v	Delay	Hysteresis	Frequency [^]	Frequency ^v		
HRF-10	3-M	AC 161 - 346 V	1	40 - 60 Hz 48 - 72 Hz 320 - 480 Hz	●	●	●	●	●	●	Switchable ranges of rated frequency .	81

Relay for factor cos-φ monitoring

Type	Design	Supply voltage	Secure variables				Setting			Description	Page
			Phases	cos φ range	> cos φ	< cos φ	Delay	Hysteresis	Memory Errors		
COS-2/230V COS-2/110V COS-2/400V COS-2/24V	3-M	AC 230 V AC 110 V AC 400 V AC/DC 24 V	3	0.1 - 0.99	●	●	●	●	●	Two output relays, one independent relay for each level Galvanically separated power supply.	82

Relay for current monitor

Type	Design	Supply voltage	Secure variables				Setting					Description	Page
			Phases	Range	> I	< I	Delay	Hysteresis	Memory Errors	> I	< I		
PRI-32	1-M	AC 24-240 V DC 24 V	1	AC 1-20 A	●	x	x	x	x	●	x	Exceeding the current value - the current flowing through the monitored conductor must not exceed 100 A even on a short-term basis.	84
PRI-41/230V PRI-41/24V	3-M	AC 230 V AC/DC 24 V	1	AC/DC 1.6 A AC/DC 5 A AC/DC 16 A	●	●	●	●	●	●	●	The adjustable delay for elimination of short-term outages and peaks for every level. Galvanically separated power supply.	86
PRI-42/230V PRI-42/24V	3-M	AC 230 V AC/DC 24 V	1	AC/DC 1.6 A AC/DC 5 A AC/DC 16 A	●	●	●	●	●	●	●	The adjustable delay for elimination of short-term outages and peaks for every level. Galvanically separated power supply.	86
PRI-51/0.5 PRI-51/1 PRI-51/2 PRI-51/5 PRI-51/8 PRI-51/16	1-M	AC 24-240 V DC 24 V	1	AC 0.05 - 0.5 A AC 0.1 - 1 A AC 0.2 - 2 A AC 0.5 - 5 A AC 0.8 - 8 A AC 1.6 - 16 A	●	x	●	x	x	●	x	May be used for scanning the current from the current transformer - up to 600A. Power supply is galvanically separated from the measured current.	85
PRI-52	1-M	AC 230 V	1	AC 0.5 - 25 A	●	x	●	x	x	●	x	May be used for scanning the current from the external current transformer - up to 600A.	88
PRI-53/1 PRI-53/5	6-M	AC/DC 24-240 V	3	AC 3 x 0.4 - 1.2 A AC 3 x 2 - 6 A	●	●	●	x	x	●	●	Monitors the drop in the strength of current below the preset value. Monitors exceeding the preset value.	89

Level switches

Type	Design	Supply voltage	Secure variables		Setting			Description	Page
			Level max.	Level min.	Delay	Sensitivity Probe	Function		
HRH-8/230V HRH-8/110V HRH-8/400V HRH-8/24V	3-M	AC 230 V AC 110 V AC 400 V AC/DC 24 V	●	●	●	●	●	Sensitivity adjustable by potentiometer. Galvanically separated power supply.	96
HRH-4/230V HRH-4/24V	set	AC 230 V AC/DC 24 V	●	●	●	●	●	Unit with no protection devices - adequate protection element needs to be integrated before the unit. Ingress protection of the assembly is IP55.	91
HRH-5	1-M	AC/DC 24-240 V	●	●	●	●	●	Measuring the frequency of 10 Hz will protect liquid from polarisation and measuring probes from increased oxidation. Galv. separated power supply.	90
HRH-6/AC HRH-6/DC	box IP65	AC 230 V AC/DC 12-24V	●	●*	●	●	●	* devices mainly designated for monitoring water level in fire-engine tanks.	92
HRH-7	box IP65	AC/DC 24-240 V	●	●	●	●	●	suitable to work in harsh conditions due to the high degree of protection IP65.	94
HRH-VS	set	230 / 400 V AC 50-60 Hz	●	●	●	●	●	Level sets placed in the control cabinet with IP65 protection (protected against dust and spraying water) where everything is already connected.	98
HRH-MS-1A HRH-MS-1.6A	set	230 / 400 V AC 50-60 Hz	●	●	●	●	●		
HRH-MS-VS-2.5A HRH-MS-VS-4A HRH-MS-VS-6.3A	set	230 / 400 V AC 50-60 Hz	●	●	●	●	●		